

MARKED-UP COPY OF SUBSTITUTE SPECIFICATION

DESCRIPTION

CONTROL DEVICE OF VEHICLE DRIVING FOR A VEHICLE MOTOR

CROSS-REFERENCE TO RELATED APPLICATION

[0001] This application is the National Phase of International Application No. PCT/JP2004/013976 filed September 16, 2004, which claims priority from Japanese Patent Application No. 2003-322510. The entire disclosures of the prior applications are incorporated by reference herein in their entireties.

BACKGROUND

Technical Field

[0002] The present invention relates to ~~to a control devices~~ device of vehicle-driving motors for a vehicle motor.

Background Art

[0003] ~~A typical type of~~ There exists a control device ef ~~for a vehicle-driving motor that includes~~ includes a torque-controlling means for controlling device that controls the torque of the vehicle-driving motor, and ~~of stall-detecting means for detecting device that detects the~~ a stalled state of the vehicle. When the stall-detecting ~~means~~ device detects a stalled state of the vehicle, the torque-controlling ~~means~~ device controls the motor so as to reduce the torque.

[0004] According to an example of such a control device, the torque of ~~the a~~ traction motor is reduced upon ~~the detection of~~ detecting the stalled state of the vehicle such that a speed or an acceleration ef ~~of of a~~ backward movement of the vehicle is less than of equal to ~~the a~~ a predetermined speed. Furthermore, an allowed time during which the vehicle remains stalled is set ~~on the basis of~~ based on the torque applied to the traction motor, and the torque is reduced ~~as above only~~ when the stalled time exceeds the allowed time (See Patent Document 1). (See, for example, Japanese Unexamined Patent Application Publication No. 7-336807 (paragraph numbers 0015 to 0021, Fig. 1)). Accordingly, the vehicle moves backward due to the torque-reducing control, and a rotor of the motor is rotated based on ~~this the torque reducing contact.~~ Thus, the current-carrying phase is switched such that the current does not intensively flow ~~intensively~~ in a particular phase.

[0005] Moreover, according to another example of the control device, when a motor 5 is determined ~~as to be~~ locked or stalled (Steps S11, 12), a restrictive torque ~~τ~~ τ_r , depending on a maximum junction temperature T_{JMAX} of a switching element of an inverter ~~circuit~~

circuit, is calculated (Step S27). When the restrictive torque τ is less than an indicative torque τ_c of the ~~motor,~~ motor and the phase range is equal to the previous state, a limited torque T_L is reduced by a displacement torque $\Delta\tau$ by subtracting $\Delta\tau$ from the restrictive torque τ (Steps S29 to S37). Accordingly, the phase range is changed so as to release the locked state (~~See Patent Document 2~~). (Japanese Unexamined Patent Application Publication No. 11-215687 (paragraph numbers 0020 to 0029, Fig. 2).

~~Patent Document 1 is Japanese Unexamined Patent Application Publication No. 7-336807 (paragraph numbers 0015 to 0021, Fig. 1). Patent Document 2 is Japanese Unexamined Patent Application Publication No. 11-215687 (paragraph numbers 0020 to 0029, Fig. 2).~~

SUMMARY

[0006] In the former control device, concentration of a current on a particular phase can be prevented by the torque-reducing process to the motor. Since the motor torque is reduced ~~on the basis of~~ based on the magnitude and the continued time of the indicative torque regardless of each temperature of the phases, the motor torque is further reduced even though the current-carrying phase on which the current is concentrated is changed to a phase whose temperature is not raised by the torque-reducing process, thus resulting in a reduction of of a driving performance of the vehicle.

[0007] In the latter control device, the torque-reducing control of the motor can be stopped by changing the current-carrying phase on which the current is concentrated. Since the motor torque is reduced ~~on the basis of~~ based on the maximum detected temperature, the motor torque is reduced in response to the temperature of the current-carrying ~~phase-phase~~, whose temperature is raised even though the current-carrying phase on which the current is concentrated is changed. Therefore, even though the current-carrying phase on which a current is concentrated is switched to one of the other two phases ~~having having a~~ having a smaller temperature rise, the motor torque is restricted and the driving performance of the vehicle is reduced.

[0008] ~~The present device is produced so as to solve the above-described problems, and an object of the present invention is to improve thus improves a driving performance and a driving feel of a stalled vehicle by reducing the torque of a motor using a temperature of a particular phase selected on the basis of~~ based on a current phase of the motor.

Disclosure of Invention

~~[0009] The present invention provides~~ According to an exemplary aspect of the invention, a control device of a vehicle motor includes a temperature sensor that detects a temperature of each coil, each coil supplying an alternating current to a corresponding phase of the motor and a controller that controls a torque of the vehicle motor; detects a stalled state of a vehicle; detects a current phase angle of the vehicle motor; and selects one of the temperatures detected by the temperature sensor based on a detected current phase angle, wherein the torque of the vehicle motor is reduced when the stalled state of the vehicle is detected and when a selected temperature exceeds a restrictive temperature.

[0010] According to another exemplary aspect of the invention, a method of operating a vehicle motor includes detecting a temperature of each coil, each coil supplying an alternating current to a corresponding phase of the motor; controlling a torque of the vehicle motor; detecting a stalled state of a vehicle; detecting a current phase angle of the vehicle motor; and selecting one detected temperature based on a detected current phase angle, wherein the torque of the vehicle motor is reduced when the stalled state of the vehicle is detected and when a selected temperature exceeds a restrictive temperature.

~~a control device of a vehicle driving motor including torque controlling means for controlling the torque of the vehicle driving motor, stall detecting means for detecting a stalled state of the vehicle, temperature detecting means for detecting temperatures of coils each supplying an alternating current to respective phases of the motor, current phase detecting means for detecting a phase of currents flowing in the motor, and temperature selecting means for selecting one of the temperatures detected by the temperature detecting means on the basis of the phase detected by the current phase detecting means. The control device is characterized in that the torque controlling means reduces the torque when the stall detecting means detects a stalled state of the vehicle and when the temperature selected by the temperature detecting means exceeds a restrictive temperature.~~

~~— [0010] — Accordingly, in a vehicle stalled on a hill, when a temperature of a phase on which a current is concentrated reaches a restrictive temperature, the torque is reduced. Accordingly, the vehicle moves slightly backward, and the current carrying phase on which~~

~~the current is concentrated is changed. When the current carrying phase is changed, a torque-reducing process is conducted on the basis of the temperature of the new current-carrying phase. Thus, the torque-reducing process is performed on the basis of the temperature of the active phase in which a current flows, and therefore the torque-reducing process is conducted less frequently compared with the known technologies in which the torque-reducing process is conducted on the basis of the indicative torque or the maximum temperature. Accordingly, gradability of the vehicle is ensured, and driving performance and driving feel of the stalled vehicle can be improved.~~

~~—— [0011] In the control device of the vehicle-driving motor according to the present invention, the temperature-selecting means selects a temperature of a predetermined phase when the phase detected by the current-phase-detecting means is within a predetermined range where a maximum current flows in the predetermined phase. Accordingly, the phase in which the maximum current flows can be exactly identified with a simple structure.~~

~~—— [0012] In the control device of the vehicle-driving motor according to the present invention, the phase is calculated on the basis of a rotational angle of the motor. Accordingly, the current phase can be derived with a simple structure.~~

BRIEF DESCRIPTION OF THE DRAWINGS

[0014] Various aspects of the invention will be described with reference to the drawings, wherein:

[0015] Fig. 1 is a block diagram illustrating a control device of a ~~vehicle-driving vehicle~~ motor according to an embodiment of the present invention;

[0016] Fig. 2 is a flow chart of a program executed in the control device shown in Fig. 1;

[0017] Fig. 3 is a flow chart of a program executed in the control device shown in Fig. 1;

[0018] Fig. 4 illustrates the relationship between the amplitude and the phase of currents in the motor shown in Fig. 1;

[0019] Fig. 5 illustrates the relationship between a torque-restricting rate and a phase temperature in the motor shown in Fig. 1;

[0020] Fig. 6 illustrates the relationship between a motor speed and a maximum torque of the motor shown in Fig. 1; and

[0021] Fig. 7 is a time chart illustrating operations executed in the control device shown in Fig. 1.

DETAILED DESCRIPTION OF EMBODIMENTS

Best Mode for Carrying Out the Invention

[0022] A control device of a ~~vehicle-driving~~vehicle motor according to an embodiment of the present invention will now be described with reference to the drawings. Fig. 1 is a block diagram illustrating the structure of the vehicle including the control device.

[0023] This vehicle is a so-called electric car including a motor 10 as a driving source, ~~and is driven by the motor 10. This source.~~ The motor 10 is a three-phase alternating-current (AC) motor, and includes stators (not shown) around which coils 11, 12, and 13 are wound. The coils 11, 12, and 13 supply the three phases of the motor, i.e. a U phase, a V phase, and a W phase, with alternating currents. The coils 11, 12, and 13 are connected to an inverter circuit 21. The inverter circuit 21 converts a direct-current (DC) voltage supplied by a battery 22 functioning as a DC power source into an AC voltage, and sequentially supplies the AC voltage to the coils 11, 12, and 13 of the U phase, the V phase, and the W phase, respectively. The motor 10 is driven by the supply of the AC voltage to the phases.

[0024] Temperature sensors 11a, 12a, and 13a are embedded in the coils 11, 12, and 13, respectively, so as to measure (~~actual~~(i.e., actual measurement) the temperatures of the respective coils. The temperatures of the coils 11, 12, and 13 detected by the respective temperature sensors 11a, 12a, and 13a, i.e. a U-phase temperature, a V-phase temperature, and a W-phase temperature, are sent to a control device 30.

[0025] Fig. 4 illustrates the relationship between the amplitude in the U phase, the V phase, and the W phase and the phase θ of currents in the motor 10. The U-phase current positively peaks when the phase θ is 0° and 360° , and negatively peaks when the phase θ is 180° . The V-phase current positively peaks when the phase θ is 120° , and negatively peaks when the phase θ is 300° . The W-phase current positively peaks when the phase θ is 240° , and negatively peaks when the phase θ is 60° . A period of each phase is 360° . Moreover, the U-phase current is set so as to positively peak when the phase θ is 0° . Also, the phases of the currents are set so as to shift from each other by 120° . This phase θ correlates with a rotational angle of the motor 10, and is calculated ~~on the basis of~~based on the rotational angle.

[0026] As shown in Fig. 1, a rotation sensor 31 for detecting the rotational angle of the motor 10 and an accelerator-aperture sensor 32 for detecting the aperture of an accelerator (not shown) of the vehicle are connected to the control device 30. The rotation sensor 31 sends the detected rotational angle of the motor 10 to the control device 30, and the control

device 30 calculates the number of revolutions of the motor 10 ~~on the basis of~~ based on the rotational angle. The accelerator-aperture sensor 32 sends the detected accelerator aperture to the control device 30, and the control device 30 determines an indicative torque T_a in the motor 10 ~~on the basis of~~ based on the rotational angle of the motor 10 and the accelerator aperture. The control device 30 sends the indicative torque T_a to the inverter circuit 21, and the inverter circuit 21 supplies the motor 10 with an alternating current depending on the indicative torque T_a .

[0027] The control device 30 includes a microcomputer (not shown), and the microcomputer includes input-output interfaces connected to the microcomputer via buses, a CPU, a RAM, and a ROM (all not shown). The CPU executes a program corresponding to a flow chart shown in Fig. 2.

[0028] In the process, one of the temperatures of the three phases is selected ~~on the basis of~~ based on the detected phase of the currents in the motor 10. When the vehicle is detected to be in a stalled state, and when the temperature of the selected phase exceeds a restrictive temperature, the torque of the motor 10 is reduced. The ROM stores the program, curves (computing equations, maps) illustrating the correlation between the amplitude and the phase θ of the currents in the motor 10 shown in Fig. 4, a map illustrating the relationship between a torque-restricting rate and a coil temperature of each phase of the motor 10 shown in Fig. 5, and a map illustrating the relationship between a maximum torque and the number of revolutions of the motor 10 shown in Fig. 6. The RAM temporarily stores the computed values relating to the control.

[0029] Next, operations of the control device of the ~~vehicle driving~~ vehicle motor having the above-described structure will now be described with reference to flow charts shown in Figs. 2 and 3. While an ignition switch (not shown) of the vehicle is on, the control device 30 executes the programs corresponding to the flow charts every predetermined short period. The control device 30 calculates an indicative torque T^* (Step 102) ~~on the basis of~~ based on the input accelerator aperture and the calculated number of revolutions of the motor 10 ~~every at a start of the program in Step 100~~ shown in Fig. 2.

[0030] Then, the control device 30 detects whether the vehicle is stalled ~~or not~~ (Step 104). When the (1) absolute value $|N|$, indicative of the number of revolutions N of the motor calculated on the basis of ~~based on~~ the input rotational ~~angle~~ angle, is less than or equal to a predetermined value N_0 (for example, 100 rpm), and when the (2) absolute value $|T^*|$ of the indicative torque ~~T^*~~ T^* , ~~calculated on the basis of~~ based on the input accelerator aperture

and the calculated number of revolutions N of the motor ~~10-10~~, is more than or equal to a predetermined value T_n , the control device 30 determines that the vehicle is stalled, ~~otherwise stalled~~. Otherwise the vehicle is not stalled.

[0031] When the vehicle is not stalled, the control device 30 determines "NO" in Step 104, and then outputs the indicative torque T^* calculated in Step 102 to the inverter circuit 21 so as to control the motor 10 at a torque depending on the indicative torque T^* in Step 106. That is to say, the control device 30 conducts an ordinary torque control. Subsequently, the program proceeds to Step 108 so as to end temporarily.

[0032] Next, when the vehicle is detected to be in the stalled state, the control device 30 determines "YES" in Step 104, and selects a phase whose temperature is to be measured ~~on the basis of~~ based on the phase θ of the currents in the motor 10 in Step 110. That is to say, the control device 30 executes a subroutine shown in Fig. 3.

[0033] In detail, the control device 30 calculates the phase θ ~~on the basis of~~ based on the rotational angle detected by the rotation sensor 31 (Step 202) ~~every at the start of the subroutine in Step 200~~. When the calculated phase θ is within a predetermined range of $-\theta_1 \leq \theta \leq \theta_1$, or $180^\circ - \theta_1 \leq \theta \leq 180^\circ + \theta_1$, i.e. within a predetermined range where a maximum current flows in the U phase, the control device 30 selects the temperature of the U phase (Steps 204, 206). Moreover, when the phase θ is within a predetermined range of $120^\circ - \theta_1 \leq \theta \leq 120^\circ + \theta_1$, or $300^\circ - \theta_1 \leq \theta \leq 300^\circ + \theta_1$, i.e. within a predetermined range where a maximum current flows in the V phase, the control device 30 selects the temperature of the V phase (Steps 210, 212). Furthermore, when the phase θ is within a predetermined range of $60^\circ - \theta_1 \leq \theta \leq 60^\circ + \theta_1$, or $240^\circ - \theta_1 \leq \theta \leq 240^\circ + \theta_1$, i.e. within a predetermined range where a maximum current flows in the W phase, the control device 30 selects the temperature of the W ~~phase.~~ phase (Steps 214, 216). In addition, when the phase θ is outside of these ranges (shaded ranges shown ~~in~~ at the bottom of Fig. 4), the control device 30 selects the highest temperature from the temperatures of the three phases (~~Steps 204, 210, 214,~~ (Step 218)). Herein, θ_1 is a predetermined value for determining a predetermined range, and is set such that the approximately maximum current flows within this predetermined range. In this embodiment, θ_1 is set to 5° .

[0034] As described above, the control device 30 selects the phase whose temperature is to be measured ~~on the basis of~~ based on the phase θ in the motor 10, which is stalled or substantially stalled, and continues executing the program to Step 208 so as to

temporarily end the subroutine process. Then, the process proceeds to Step 112 shown in Fig.

2. The control device 30 detects the temperature T of the selected phase in Step 112.

[0035] When the temperature T detected in Step 112 is less than a restrictive temperature T_s , the control device 30 conducts the ordinary torque control ~~as described above~~ (Steps 114, 116, 106). In detail, the control device 30 calculates a torque-restricting rate η (%) from the map illustrating the relationship between the torque-restricting rate and the coil temperature (phase temperature) shown in Fig. 5 and the detected phase temperature of the selected phase in Step 114. Then, in Step 116, the control device 30 calculates the product of the maximum torque T_{max} ~~calculated based on depending on~~ the number of revolutions of the motor 10 ~~calculated from and~~ the curve shown in Fig. 6, and the torque-restricting rate η , calculated as described above, ~~and with~~ the quotient of the value divided by 100 (i.e. a restrictive torque, or the maximum torque that can be output at the temperature and the number of revolutions); and compares the result with the indicative torque T^* . When the indicative torque T^* is less than or equal to the restrictive torque, the control device 30 conducts the ordinary torque control using the indicative torque T^* .

[0036] On the contrary, when the temperature T is more than or equal to the restrictive temperature T_s , the control device 30 calculates a reduced indicative torque for setting a torque lower than that of the ordinary control conducted until immediately before, and outputs the calculated indicative torque to the inverter circuit 21 so as to control the motor 10 at a torque depending on the reduced indicative torque (Steps 114 to 118, 106). That is to say, the control device 30 reduces the torque. In detail, the control device 30 calculates the torque-restricting rate η (%) as described above (Step 114), and compares the restrictive torque with the indicative torque T^* (Step 116). When the indicative torque T^* exceeds the restrictive torque, the control device 30 sets the restrictive torque as a new indicative torque T^* (Step 118). In both cases, the program proceeds to Step 108 so as to end temporarily. A reduced indicative torque T_b is preferably set such that the vehicle gradually moves back.

[0037] Next, operations of a vehicle including the control device operating as above will now be described with reference to Fig. 7. Fig. 7 is a time chart illustrating the temperatures of the three phases in the motor 10, the temperature of the selected phase, and the position of the vehicle, respectively, from top to bottom.

[0038] When the vehicle on a hill is stalled at time t_0 due to a balance between a backward movement by the weight of the vehicle and a forward movement by the torque of

the motor 10, a phase whose temperature is to be detected is selected (Steps 102, 110). In the example shown in Fig. 7, the phase θ of the currents in the stalled motor 10 ranges within $-\theta_1 \leq \theta \leq \theta_1$. Accordingly, the U phase is selected for the temperature detection. Immediately after the motor is stalled, the U-phase temperature is considerably lower than the restrictive temperature T_s . The vehicle remains halted at a stopping position A until the U-phase temperature exceeds the restrictive temperature T_s . Since the motor 10 is stalled while the phase θ ranges within $-\theta_1 \leq \theta \leq \theta_1$ after time t_0 , most of the current flows in the U phase, and the U-phase temperature rises at a faster rate than those of the other phases.

[0039] When the U-phase temperature exceeds the restrictive temperature T_s at time t_1 , the control device 30 calculates an indicative torque lower than that up to time t_1 (Step 116), and controls the motor 10 at the indicative torque (Step 106). Consequently, the torque of the motor 10 is reduced, and the vehicle, which was halted up to time t_1 due to the balance, moves backward. As a result, the vehicle is released from the stalled state and determined as unstalled, and an ordinary torque control is conducted (Steps 102, 104). Accordingly, the vehicle gradually stops the backward movement when the phase in which the current flows changes, is re-stalled at time t_2 , and stops at a stopping position B.

[0040] At time t_2 , the control device 30 determines that the vehicle is stalled as in the case of time t_0 , and selects a phase whose temperature is to be detected (Steps 102, 110). During a period from time t_1 to time t_2 , the phase θ advances by substantially 60° due to a slight backward movement of the vehicle, and the vehicle stops in this state. Accordingly, the phase θ ranges within $60^\circ - \theta_1 \leq \theta \leq 60^\circ + \theta_1$, and thus the W phase is selected for the temperature detection. At time t_2 , the W-phase temperature is higher than that at the start of the stalled state (time t_0). However, the W-phase temperature is the lowest of those of the three phases, and is lower than the restrictive temperature T_s . Therefore, the vehicle remains halted at the stopping position B until the W-phase temperature exceeds the restrictive temperature T_s . Since the motor 10 is stalled while the phase θ ranges within $60^\circ - \theta_1 \leq \theta \leq 60^\circ + \theta_1$ after time t_2 , most of the current flows in the W phase, and the W-phase temperature rises at a faster rate than those of the other phases.

[0041] When the W-phase temperature exceeds the restrictive temperature T_s at time t_3 , the control device 30 reduces the torque of the motor 10 as in the case of time t_1 . Thus, the vehicle, which was halted up to time t_3 due to the balance, moves backward. Subsequently, the ordinary torque control is conducted to the vehicle, the vehicle is re-stalled at time t_4 , and stops at a stopping position C.

[0042] At time t_4 , the control device 30 determines that the vehicle is stalled as in the case of time t_0 , and selects a phase whose temperature is to be detected (Steps 102, 110). During a period from time t_3 to time t_4 , the phase θ advances by substantially 60° due to a slight backward movement of the vehicle, and the vehicle stops in this state. Accordingly, the phase θ ranges within $120^\circ - \theta_1 \leq \theta \leq 120^\circ + \theta_1$, and thus the V phase is selected for the temperature detection. At time t_4 , the V-phase temperature is higher than that at the start of the stalled state (time t_0). However, the V-phase temperature is lower than the restrictive temperature T_s . Therefore, the vehicle remains halted at the stopping position C until the V-phase temperature exceeds the restrictive temperature T_s . Since the motor 10 is stalled while the phase θ ranges within $120^\circ - \theta_1 \leq \theta \leq 120^\circ + \theta_1$ after time t_4 , most of the current flows in the V phase, and the V-phase temperature rises at a faster rate than those of the other phases.

[0043] When the V-phase temperature exceeds the restrictive temperature T_s at time t_5 , the control device 30 reduces the torque of the motor 10 as in the case of time t_1 . Thus, the vehicle, which was halted up to time t_5 due to the balance, moves backward.

[0044] The above-described process is repeated until all the phase temperatures exceed the restrictive temperature T_s . When all the phase temperatures exceed the restrictive temperature T_s , the torque-reducing control is continuously conducted, and thus the vehicle continues moving backward.

[0045] As described above, when a temperature of a phase in a stalled vehicle reaches the restrictive temperature T_s , the vehicle moves backward due to the reduced torque, and the phase θ is shifted. When the vehicle is re-stalled, a phase whose temperature does not reach the restrictive temperature T_s can be used until all the phase temperatures exceed the restrictive temperature T_s .

[0046] In the above-described embodiment, the motor 10 is stalled within predetermined ranges of the phase θ where a maximum current flows. When the motor 10 is stalled outside the predetermined ranges of the phase θ (shaded ranges shown in Fig. 4), a phase having a maximum temperature may be selected from the three phases (Steps 200 to 204, 210, 214, 218), the temperature may be detected (Step 112) and compared with the restrictive temperature T_s (Step 114), and the torque may be controlled depending on the comparison (Steps 116, 104).

[0047] As is clear from the above-described description, according to this embodiment, when a temperature of a phase in a vehicle stalled on a hill reaches the

restrictive temperature T_s , the torque is ~~reduced~~, reduced and the vehicle moves slightly backward. Then, the phase in which the current flows ~~changes~~, changes and the vehicle is re-stalled. At this time, when the temperature of the particular phase selected according to the phase θ in the motor 10 in this state does not reach the restrictive temperature T_s , the control device 30 compares the phase temperature and the restrictive temperature T_s . Whereas the phase temperature reaches the restrictive temperature T_s , the control device 30 repeats the torque-reducing process until the motor 10 stops at a phase temperature less than the restrictive temperature T_s . Thus, compared with the known technologies in which a time period before a torque-reducing control starts in one of the phases is short, gradability of the vehicle is ensured for a long period of time before the torque-reducing control starts in all the phases. Therefore, a driving performance and a driving feel of the stalled vehicle can be improved.

[0048] Moreover, the control device 30 selects a temperature of a predetermined phase when the detected phase θ is within predetermined ranges where a maximum current flows in the predetermined phase. Accordingly, the phase in which the maximum current flows can be exactly identified with a simple structure. Furthermore, since the phase θ is calculated ~~on the basis of~~ based on the rotational angle of the motor, the phase θ can be derived with a simple structure.

[0049] In the above-described embodiment, the three temperature sensors 11a, 12a, and 13a for measuring the temperatures of the three coils are employed ~~as~~ as a temperature-detecting ~~means~~, device. However, only the temperature of one of the plurality of coils may be measured by a temperature sensor, and the temperatures of the other coils may be estimated ~~on the basis of~~ based on the measured value. In this manner, the temperatures of all the phases can be detected with a simple structure.

[0050] Moreover, in the above-described embodiment, the motor 10 is a three-phase AC motor. However, the motor 10 may be an AC motor having a plurality of phases.

[0051] Furthermore, in the above-described embodiment, the relationship between the currents in the U phase, the V phase, and the W phase and the phase θ in the motor 10 is not limited to that set above. The phases θ of the currents at which the amplitudes peak may be set to arbitrary values as long as each of the amplitudes shifts from each other by 120° .

Industrial Applicability

[0052] As described above, the control device of the ~~vehicle-driving~~ vehicle motor according to the present invention utilizes the temperature of the particular phase selected ~~on~~

~~the basis of~~based on the phase of currents in the motor to reduce the torque of the motor, and is applicable to a case for improving the driving performance and the driving feel of the stalled vehicle.

[0053] According to an exemplary aspect of the invention, in a vehicle stalled on a hill, when a temperature of a phase on which a current is concentrated reaches a restrictive temperature, the torque is reduced. Accordingly, the vehicle moves slightly backward, and the current-carrying phase on which the current is concentrated is changed. When the current-carrying phase is changed, a torque-reducing process is conducted based on the temperature of the new current-carrying phase. Thus, the torque-reducing process is performed based on the temperature of the active phase in which a current flows, and therefore the torque-reducing process is conducted less frequently compared with the known technologies in which the torque-reducing process is conducted based on the indicative torque or the maximum temperature. Accordingly, gradability of the vehicle is ensured, and driving performance and driving feel of the stalled vehicle can be improved.

[0054] According to another exemplary aspect of the invention, the phase in which the maximum current flows can be exactly identified with a simple structure.

[0055] According to another exemplary aspect of the invention, the current phase can be derived with a simple structure.